

METHOD AND SYSTEM FOR ACCOMPLISHING PRODUCT DETECTION

This application is based on Provisional Application No. 60/271,998, filed February 27, 2001. This application includes subject matter protected by
5 copyright.

BACKGROUND OF THE INVENTION**Technical Field**

The present invention relates to the vending arts generally and more specifically to vending machine
10 delivery systems for determining whether a product has actually been delivered to the consumer after a customer order.

Description of the Prior Art

Currently, vending machines lack the ability to
15 detect and confirm whether an ordered product has been actually delivered to a customer after an ordered vend event by the customer has occurred. Present methods, referred herein as the home switch method, always assume that the ordered product is available for delivery and
20 that the product is successfully delivered upon completing one vend cycle.

However, vending machines often fail to deliver the product after the vend cycle for various reasons, including improper installation of the products by the

vendor's sales representative or obstructions in the delivery path. Thus, presently, after paying for the product and a vend cycle occurring, the customer fails to receive the ordered product, resulting in the customer becoming frustrated with the vending company, affecting customer relations and vending sales.

1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 2693 2694 2695 2696 2697 2698 2699 2700 2701 2702 2703 2704 2705 2706 2707 2708 2709 2710 2711 2712 2713 2714 2715 2716 2717 2718 2719 2720 2721 2722 2723 2724 2725 2726 2727 2728 2729 2730 2731 2732 2733 2734 2735 2736 2737 2738 2739 2740 2741 2742 2743 2744 2745 2746 2747 2748 2749 2750 2751 2752 2753 2754 2755 2756 2757 2758 2759 2760 2761 2762 2763 2764 2765 2766 2767 2768 2769 2770 2771 2772 2773 2774 2775 2776 2777 2778 2779 2780 2781 2782 2783 2784 2785 2786 2787 2788 2789 2790 2791 2792 2793 2794 2795 2

BRIEF SUMMARY OF THE INVENTION

A vending system that verifies the delivery of a ordered product using a product delivery system that sends a product from a first storage position through a delivery path to a second receiving position, a sensing system located along the delivery path that senses when the product passes a sensor during the product transition through the delivery path from the first position to the second position, and a reporting circuitry electronically coupled to the sensing circuitry wherein the reporting circuitry reports to the product delivery system when the product has passed through the sensing system.

Additionally, a vending machine method is provided for determining whether a product is delivered, the method comprising the steps of sending a delivery signal based on a customer ordering event to a product delivery system, monitoring a delivery path that the product travels to reach a product receiving location, and determining if the product was delivered to the receiving space.

The foregoing has outlined some of the more pertinent objects and features of the present invention. These objects should be construed to be merely illustrative of some of the more prominent features and

applications of the invention. Many other beneficial results can be attained by applying the disclosed invention in a different manner or modifying the invention as will be described. Accordingly, other
5 objects and a fuller understanding of the invention may be had by referring to the following Detailed Description of the Preferred Embodiment.

013039.00090:594534.05

BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 is an overview of the methodology utilized in the present invention;

Figure 2 shows a schematic diagram of the present
5 invention;

Figure 3A shows the emitter arm portion of the monitoring system;

Figure 3B shows the detector arm portion of the monitoring system;

10 **Figure 4** shows the operation of the monitoring system when a customer places an order;

Figure 5 shows the steady state calibration mode of the monitoring system;

15 **Figure 6** shows a typical detector arm attached to a vending machine; and

Figure 7 shows light beam patterns for the emitters in the monitoring system.

DETAILED DESCRIPTION

The present invention is a vending system that verifies that an actual delivery of an ordered product is made. If the actual delivery fails for a set number of
5 delivery attempts, then the customer is offered one or more alternative choices, including without limitation, choosing an alternative product, or a refund.

Figure 1 is an overview of the methodology utilized in the present invention. The monitoring system is in
10 calibration mode in its normal steady state configuration mode as shown in step 100. Calibration mode is discussed in greater detail in **Figure 5** below. The customer orders a product after placing money in the ordering system by depressing a keypad or similar device in step 102. The
15 vending machine's ordering system sends a customer order event signal in step 103 to the monitoring system informing the sensing/monitoring system that an order event has occurred in step 102. The monitoring system subsequently completes its last calibration cycle in step
20 104 and transitions from steady state calibration mode to the monitoring cycle in step 106. Upon transitioning, the monitoring system commences its sensing/monitoring cycle by monitoring the product delivery path and sends a ready signal to the product delivery system in step 110.

The monitoring cycle is described in more detail in **Figure 4**, herein below. After receiving a ready signal from the monitoring system, the product delivery system attempts to deliver a product through the product delivery path in step 120. If the monitoring system senses or detects the product passing through the delivery path in step 125, it reports the delivery event to the ordering system in step 130. Upon receiving the report, the ordering system concludes the transaction with the customer and sends a completion signal to the monitoring system, which returns to steady state calibration mode in step 135, whereupon the monitoring system enters into calibration mode in step 140.

If the monitoring system does not detect a product in the first delivery attempt in step 125 then it will not send a signal to the ordering system after the step 125. The invention allows the delivery system to attempt delivery three times or a preset option. In step 150, if the number of attempted delivery cycles is less than the preset option, then the ordering system thereupon attempts to deliver the product again in step 120. If the attempted delivery cycles equal the preset option, then in step 155 the customer is granted alternatives to purchasing the first ordered product. Step 155 allows

the customer to either ask for a refund or make a selection of a second, different product for delivery and step 153 marks the first ordered product as empty.

Step 153 prevents future vend attempts for the first
5 ordered product until the vending machine is visited by a service person. This helps to prevent cheating by a customer if the vending machine reverts to the home switch operation, and helps to prevent further tampering if tampering was the cause of the first vend failure.

10 If the customer chooses a refund, then the present invention delivers a signal to make a refund, in step 160, whereupon a signal is sent to the monitoring system that the order is complete in step 135 and to the monitoring system to enters into steady state calibration
15 mode in step 140. If the customer choose a second, different product, then the present invention returns to 120 and the process proceeds as described above, until the operation is complete.

Figure 2 shows a schematic diagram of the present
20 invention installed in a vending machine 205. In **Figure 2** various products 210 are placed in the vending machine's delivery system 215. Prior to a customer making a purchase, the monitoring system 217 is in calibration mode. When a customer makes an order through

the order system 220, the monitoring system completes the calibration mode and enters into its monitoring mode. Thereupon, the ordering system allows for an attempted delivery of the ordered product 210, typically through a helical delivery system 215. When ordered, product 270 is delivered into delivery space 222, falling through the delivery path 225 past monitoring system 217. As it passes the monitoring system, the product momentarily breaks the continuity of the monitoring system's monitoring devices. If the monitoring system utilizes an optical monitoring system, then as the product passes through the monitoring system's light plane 234, be it infrared or otherwise, it momentarily breaks the light continuity and prevents a portion of the light from reaching at least one detector on the opposite side of the monitoring path. The logic circuit on the detecting arm 235 will note the momentary blockage of light and report it as a delivery event.

The monitoring system is comprised of an emitter arm 240 upon which are located a set number of one or more emitters 242, and a detector arm 250 comprising of one or more detectors 252 and located directly across delivery path 225 from the emitter arm 240. Emitter signals, the total of which comprise light plane 234 are sent from the

emitters 242 to the detectors 252 across the delivery path 225, during both monitoring mode and calibration mode. The emitter arms and detector arms are described in more detail in **Figures 3A**, and **3B**.

5 **Figure 3A** shows the emitter arm portion of the monitoring system. In **Figure 3A**, emitting arm 310A transverses along one side of the delivery path in the vending machine. Emitters, 315A, are attached to arm 310A. The horizontal and vertical placement of emitters
10 315A on arm 310A is determined by the size of the smallest product that crosses the delivery path, and by the type and accuracy of the emitters utilized in the present invention.

The emitters may comprise of an optical monitoring
15 device. The spacing of optical emitters is determined by five factors: emitter size, optical diffusion, ambient light, product size and the reflected light. Emitter size and optical diffusion is fixed at the time of construction, however, ambient and reflective light may
20 vary over the course of use of the emitter. Infrared light may be used to help to reduce these effects, however, it is clearly understood and contemplated by the present invention that other types of light sources can be used, including various lasers or white light sources.

The body 320A of the arm 310A is made of suitable material able to contain the electronic control components 325A necessary to operate the emitter, including, a power source 330A, and logic circuitry 335A.

5 Additionally, holes 340A are provided to securely fasten and adjust the positioning of the arm 310A to the vending machine.

Figure 3B shows the detector arm portion of the monitoring system. The shape and construction of the

10 detecting arm 350B is related to the shape and construction of the emitting arm 310A. The detecting arm 350B is placed on the same plane, parallel to and across the delivery path from arm 310A (see **Figure 2** for more details). The detectors 355B are arranged so that their

15 vertical spacing and horizontal arrangement mirror the emitter's arrangement on arm 310A. Likewise, the body 360B of 350B is constructed of material suitable to contain detection and logic circuitry 365B, attachment holes 370B, and a power source 375B. The choice of the

20 type of detector is directly related to the type of emitter being utilized in the present invention.

Figure 4 shows the operation of the monitoring system when a customer places an order. Prior to placing an order, the monitoring system is in calibration mode in

step 400. Upon placement of the order in step 405, the monitoring system transitions from its steady state calibration mode 400 into its monitoring mode in step 407. Once in monitoring mode, the monitoring system
5 begins cycling each emitter by pulsing the emitter individually in step 410. The monitoring system uses a pulse strength determined from when the system was in the calibration mode.

In step 410 an emitter pulses its signal to the
10 corresponding detector across from the emitter, and the two detectors on either side of the detector. Upon pulsing the light, the detector circuitry determines whether the detectors detected the light from the emitter in step 415. (If the emitter is either the first emitter
15 or the last emitter on the emitter arm, then only the detector across from the emitter and the detector on the non-wall side of the detector is scanned.)

If the detector directly across from the pulsing emitter or the side detectors detects the signal in 415,
20 then the emitter's logic circuit sequences to the next emitter in line and sends a pulse from that emitter in step 420. The emitter's logic circuit continues until after it completes the pulsing of the last detector whereupon, the monitoring system repeats the process,

begins again at the first emitter until the detector's logic circuit receives a detect signal and the monitoring system receives a signal to cease monitoring.

If at least one of the three detectors fails to
5 detect a light beam from the emitter during the monitoring cycle, then the logic circuit reports a product delivery to the ordering system in step 425. Once a report of delivery is made to the ordering system, the ordering system returns a signal to the monitoring
10 system to return to steady state calibration mode in step 430. Otherwise, the monitoring system continues to monitor until it receives a return to steady state calibration signal from the ordering system because of a refund, if appropriate.

15 **Figure 5** shows the steady state calibration mode of the monitoring system. During the steady state calibration mode, the monitoring system is constantly calibrating itself for optimum performance because temperature, humidity, dust, and alignment conditions
20 fluctuate over the course of system usage.

The calibration mode adjusts the light intensity from each emitter as necessary so that each set of three detectors serviced by that emitter receives only enough intensity, plus a small safety margin, to be active in

the unblocked condition. This minimizes the adverse affects of reflected light from the emitters and allows for a wider detector aperture (which makes system alignment easier) and reduces the overall power requirements of the system. In step 505, the logic circuit in the monitoring system determines whether an order has been placed. If an order has not been placed, then the monitoring system proceeds to send a series of pulses to the first of the one or more emitters in step 510. Upon sending a pulse, the monitoring system queries the emitter's corresponding detector and each detector on either side of the corresponding detector to determine if those detectors detected the pulsed signal in step 515. If a signal was detected in each of the three detectors then the monitoring circuitry sequences to the next emitter in step 520. The emitter's typically have adjustable signal power levels associated with the type of emitter used. The calibration mode will attempt to maintain the power level at the level needed to provide just enough signal, plus a safety margin, such that the corresponding detectors detect the signal. If any one of the three detectors does not detect the pulsed signal from the emitter, then in step 530, the monitoring circuitry determines whether the emitter is operating at

its maximum power intensity. If the emitter is not, then the emitter will step increase the signal power level in step 560 and re-send a pulsed signal to the detectors again in step 510. If the power intensity for that emitter is at its maximum intensity, then the detector will send an error message to the monitoring system in step 540. The monitoring system will then follow a pre-coded routine to shut down the entire vending operation, shut down the monitoring system or rely on prior art ordering systems (the home switch method) in step 550.

Figure 6 shows a typical detector arm attached to a vending machine. Because of the reflective surfaces 610 in the vending machine, small apertures 620 are used to minimize the reflective light from adjacently reflective surfaces 610. The apertures are narrowed holes located in front of the detectors, 625, on the detector side of sensing system 630. The holes inhibit unwanted reflections from adjacent surfaces by blocking much of the light beams that reflect back to the detector arm at wider angles than the apertures allow.

Apertures 620 keep the majority of the unwanted light from reaching the detection side of the monitoring system. In addition, the detectors 630 have a usable 60-degree horizontal/30 degree vertical reception angle.

Light arriving at the detector at angles greater than these is rejected. Additionally, infrared optical detectors contain optical frequency filters, which reject visible light frequencies, but pass the infrared frequencies of interest. Modulation techniques, whereby the detector only responds to certain signal frequencies from the infrared emitters may also be used to allow the detectors to distinguish between the ambient light and the desired point source light frequency from the emitter.

As mentioned above, product detection may be accomplished by utilizing infrared emitter/detector pairs that can monitor and detect when a signal path is broken. In typical a vending machine's delivery paths, a set of ten infrared emitter/detector pairs are used to cover the delivery path much like a light curtain.

Figure 7 shows a representative example of a light curtain 730 that may be utilized in the present invention. Typically, nine sets of emitters/detectors are used to cover the main delivery path, while the tenth set is used to cover a gum/mint area. The nine sets that cover the main delivery path implement a technique, which, other than for the first and last emitter, requires that, a minimum of three detectors are active

for each individual emitter monitor cycle. For those vending machines without a gum or mint section, the tenth emitter may be used for the main delivery area, provided that proper alignment of the ten sets is taken into
5 consideration.

This arrangement is illustrated in **Figure 7**, which shows the light beams 710 of interest for each emitter 720 and detector 725. The spacing of the emitter/detector sets are chosen to assure that the
10 smallest size traditional product breaks the path of at least one beam when it crosses the light curtain during delivery. The technique of servicing three detectors for each emitter, allows the monitor to read multiple light beams, which further reduces this spacing in the majority
15 of the delivery area. A logic circuit determines whether a light beam has been broken.

In the monitoring system, the infrared emitter/detector sets are controlled by a micro-controller located on the detector arm. During the
20 monitoring mode, it is necessary to monitor each of the emitter/detector sets separately because of the potential for light bleed-over from adjacent emitters. The timing sequence for each set monitor cycle used during the monitoring mode must be fast enough to ensure that the

smallest product will be detected by any one of the detectors when the product passes the monitor plane as it falls from the product storage area.

The control software further provides the vending operator an option to revert to home switch operation or to place the vending machine out of service in the event the monitoring system is inoperative. This allows the operator to choose one of two options if the monitoring system is operative: 1. to go out-of-service and thus assure that the customer is cheated since the monitoring system cannot determine proper delivery of a ordered product by home switch operation; or 2. to continue making selections available to the customer under the traditional home switch operation with the risks of non-proper delivery of product that operation implies.

The monitoring system controller printed circuit board uses flash memory to store the firmware. This gives the option to perform firmware updates in the field.

The vending system has several operating options. These may be viewed and programmed by pressing the PRODUCT CONFIG service key on the keypad located on the inside of the vending machine and pressing the down arrow until the appropriate option is reached. The keypad has an associated display device, such as an led screen or

such other typical devices that allow the operator to view the code and results stored within the system.

By depressing the EDIT key, the vendor can choose between "SURE.V ON" or "SURE.V OFF". "SURE.V OFF" is
5 chosen by the operator only if the monitoring system is not installed or if the operator does not wish it to use it at the present time. The remaining options for the PRODUCT CONFIG mode are only visible if "SURE.V ON" is selected and the monitoring system is available.

10 When "SURE.V ON" is selected, the operator may then choose between "OPT'N SURE.V" or "MUST SURE.V". If "OPT'N SURE.V" is selected, the vending machine operation reverts to home switch operation if the monitoring system is not operating normally because, for example, of an
15 obstruction or loss of communication. If "MUST SURE.V" is selected by the operator, the vending machine operates only if the monitoring system is available for use for the main delivery area. (The gum and mint area does not affect operation of the main area, unless the programmer
20 decides otherwise.) Otherwise, the vending machine becomes temporarily out-of-service until the blockage or other error is corrected.

When the operator uses the number keys to program "ANTI.JP xx", the anti-jackpot protection option against

unforeseeable cheating of the vending machine's monitoring system is activated. "xx" represents the number of empty conditions that disables the entire delivery system for a time period as programmed and
5 decided by the operator (described below). A empty condition occurs when product delivery is not detected and the customer's money is restored or returned. An "xx" value of "00" disables this anti-jackpot feature.

The assumption of this option is that very few
10 system failures to the vending machine's delivery system occurs. If a significant number of failures, represented by "xx", do occur then it is assumed that it is because of tampering. Upon reading "xx", the delivery system is deactivated for a certain amount of time so that money
15 can no longer be refunded because of a vend failure and to discourage a potential thief from attempting to steal either product or money.

In this condition, the vending machine either reverts to home switch operation if "OPT'N SURE.V" is
20 active, or the system deactivates and the vending machine goes out of service if "MUST SURE.V" is active. If in "Must Sure.V", once the programmed deactivation time has elapsed the system is re-enabled and the count towards "xx" is restarted. The total number of system empty

selections, the number of anti-jackpot occurrences, and the date and time of the last occurrence are recorded as noted below.

The operator programs the number of minutes that the vending system remains disabled because of an anti-jackpot occurrence by selecting the "AJP.TMR xxM" option where "xx" is the time in minutes. If "99" is programmed, then the system remains disabled until the main door closes at the end of the next service call.

10 Closing the main door also resets any anti-jackpot time remaining.

Certain system data can be reviewed in the PRODUCT CONFIG mode:

"SV.EMPTY xx" returns the number of times that credit was restored or returned because the monitoring system failed to detect a product delivery.

15

"**.SV xxxx" returns the total number of corrected vends, viewable by selection. These are the vends, which normally would not have delivered product if the present invention was not active.

20

"WO.SV xxxx" returns the number of vends, viewable by selection, made while the monitoring system was disabled for some reason.

The MACHINE CONFIG list provides additional options
5 related to the present invention. If the operator selects "FAIL=CASH", the customer's money is automatically returned on any failed vend. If "FAIL=CRDT" is selected, the credit is restored to the vending machine for another selection. The customer may
10 press the coin return to retrieve his money.

The TEST list provides the test screen for the system. If the operator keys in "SV.TST xxx", the following options are provided:

"SV.TST OK" indicates that the monitoring system is
15 operating properly.

"SV.TST xx" indicates a block in sensing zone 1-9 with 1 being closest to the glass. "H" indicates the gum & mint is blocked if it is configured. This number is displayed real-time and beeps as it changes. This may be used to
20 test the product coverage of the monitoring system's sensors, although the accuracy is somewhat less than in actual vend situations because of the data being presented.

"SV.TST CAL" indicates calibration values that are high. "EDIT" may be used to view the calibration values. A high calibration may be caused by dirt, misalignment of the system sensors, or a partial blockage of a sensor.

5 A calibration value of "0" indicates a shorted detector. This normally requires a new detector assembly.

10 A calibration value of "1" indicates that zone could not be calibrated. It indicates a blocked or damaged sensor.

Calibration values above "A" are abnormal and may require adjustment of the alignment or cleaning of the sensors.

15 "SV.TST COMM" indicates loss of communication with the monitoring system, and allows the operation to check the harness connections between the vending machine controller and the monitoring system's controller.

Diagnostics related to the present invention:

20 "SV.EMPTY nn" shows that selection "nn" was marked as empty because product delivery was not detected.

"SV.TST xx" automatically enters the system test screen as a diagnostic message if any blocked sensor, communication error, or calibration error is detected.

"AJP.TMR xx.xM" is in the diagnostic list if the anti-jackpot timer is active. It shows the time remaining.

"AJP xxX MN/DY HR.MN" is the total number of times the anti-jackpot feature occurred plus the date and time of the last occurrence.

13039:90